



# Wholesale Platform TOS/NC/NCI/SECNCI Combination Order Matrix

## Acquired West Virginia Service Territory

Type of Service (LSR.TOS)	Network Channel Code (LSR.NC)	Network Channel Interface Code (LSR.NCI)	Secondary Network Channel Interface Code (LSR.SECNCI)	Description
1EM-	(Blank)	(Blank)	(Blank)	Centrex Loop Start
1CM-	(Blank)	(Blank)	(Blank)	Coin Loop Start
1TM-	(Blank)	(Blank)	(Blank)	Public Access Line (PAL)
1PM-	(Blank)	(Blank)	(Blank)	Line Split- migrate voice, retain existing data provider (SDP=B)
2PM-	(Blank)	(Blank)	(Blank)	Line Split- migrate voice, retain existing data provider (SDP=B)
1PM-	URC-	04QSM.L05	02DUM.LS5	Bus Loop Start ADSL-C Line Splitting HFLP 6KFT Bridge Tap Total Cable 12kft (SDP=A) <sup>1 2</sup>
1PM-	URC-	04QSM.L05	02DUM.GS5	Bus Ground Start ADSL-C Line Splitting HFLP 6KFT Bridge Tap Total Cable 12kft (SDP=A) <sup>1 2</sup>
1PM-	URR-	04QSM.L05	02DUM.GS5	Bus Ground Start ADSL-R Line Splitting HFLP 6KFT Bridge Tap Total Cable 18kft (SDP=A) <sup>1 2</sup>
1PM-	URR-	04QSM.L05	02DUM.LS5	Bus Loop Start ADSL-R Line Splitting HFLP 6KFT Bridge Tap Total Cable 18kft (SDP=A) <sup>1 2</sup>
1PM-	URCN	04QSM.L05	02DUM.LS5	Bus Loop Start ADSL-C Line Splitting HFLP Zero Bridge Tap Total Cable 12KFT (SDP=A) <sup>1 2</sup>
1PM-	URCN	04QSM.L05	02DUM.GS5	Bus Ground Start ADSL-C Line Splitting HFLP Zero Bridge Tap Total Cable 12KFT (SDP=A) <sup>1 2</sup>
1PM-	URRN	04QSM.L05	02DUM.LS5	Bus Loop Start ADSL-R Line Splitting HFLP Zero Bridge Tap Total Cable 18KFT (SDP=A) <sup>1 2</sup>
1PM-	URRN	04QSM.L05	02DUM.GS5	Bus Ground Start ADSL-R Line Splitting HFLP Zero Bridge Tap Total Cable 18KFT (SDP=A) <sup>1 2</sup>
2PM-	URC-	04QSM.L05	02DUM.LS5	Res Loop Start ADSL-C Line Splitting HFLP 6KFT Bridge Tap Total Cable 12kft (SDP=A) <sup>1 2</sup>
2PM-	URC-	04QSM.L05	02DUM.GS5	Res Ground Start ADSL-C Line Splitting HFLP 6KFT Bridge Tap Total Cable 12kft (SDP=A) <sup>1 2</sup>
2PM-	URR-	04QSM.L05	02DUM.GS5	Res Ground Start ADSL-R Line Splitting HFLP 6KFT Bridge Tap Total Cable 18kft (SDP=A) <sup>1 2</sup>
2PM-	URR-	04QSM.L05	02DUM.LS5	Res Loop Start ADSL-R Line Splitting HFLP 6KFT Bridge Tap Total Cable 18kft (SDP=A) <sup>1 2</sup>

Revised: 06/12/2018



## Wholesale Platform TOS/NC/NCI/SECNCI Combination Order Matrix Acquired West Virginia Service Territory

Type of Service (LSR.TOS)	Network Channel Code (LSR.NC)	Network Channel Interface Code (LSR.NCI)	Secondary Network Channel Interface Code (LSR.SECNCI)	Description
2PM-	URCN	04QSM.L05	02DUM.LS5	Res Loop Start ADSL-C Line Splitting HFLP Zero Bridge Tap Total Cable 12KFT (SDP=A) <sup>1 2</sup>
2PM-	URCN	04QSM.L05	02DUM.GS5	Res Ground Start ADSL-C Line Splitting HFLP Zero Bridge Tap Total Cable 12KFT (SDP=A) <sup>1 2</sup>
2PM-	URRN	04QSM.L05	02DUM.LS5	Res Loop Start ADSL-R Line Splitting HFLP Zero Bridge Tap Total Cable 18KFT (SDP=A) <sup>1 2</sup>
2PM-	URRN	04QSM.L05	02DUM.GS5	Res Ground Start ADSL-R Line Splitting HFLP Zero Bridge Tap Total Cable 18KFT (SDP=A) <sup>1 2</sup>
1BMR	(Blank)	(Blank)	(Blank)	Business Remote Call Forward
2BMR	(Blank)	(Blank)	(Blank)	Residential Remote Call Forward
1BM-	(Blank)	(Blank)	(Blank)	Business single or multi-line without hunting
2BM-	(Blank)	(Blank)	(Blank)	Residential single or multi-line without hunting
1AM-	(Blank)	(Blank)	(Blank)	Business multiline with hunting
2AM-	(Blank)	(Blank)	(Blank)	Residential multiline with hunting
1AML	(Blank)	(Blank)	(Blank)	Install, Migrate or Disconnect Shared Broadband + Voice: Bus with hunting (ACT=N, V; ACT=C+LNA=N; ACT=D)
1BML	(Blank)	(Blank)	(Blank)	Install, Migrate or Disconnect Shared Broadband + Voice: Bus without hunting (ACT=N, V; ACT=C+LNA=N; ACT=D)
2AML	(Blank)	(Blank)	(Blank)	Install, Migrate or Disconnect Shared Broadband + Voice: Res with hunting (ACT=N, V; ACT=C+LNA=N; ACT=D)
2BML	(Blank)	(Blank)	(Blank)	Install, Migrate or Disconnect Shared Broadband + Voice: Res without hunting (ACT=N, V; ACT=C+LNA=N; ACT=D)
1BBL	(Blank)	(Blank)	(Blank)	Disconnect or Change Shared Broadband + Voice (when change impacts BB) Bus without hunting (ACT=C; ACT=D)
2BBL	(Blank)	(Blank)	(Blank)	Disconnect or Change Shared Broadband + Voice (when change impacts BB) Res without hunting (ACT=C; ACT=D)
1ABL	(Blank)	(Blank)	(Blank)	Disconnect or Change Shared Broadband + Voice (when change impacts BB) Bus with hunting (ACT=C; ACT=D)

Revised: 06/12/2018



# Wholesale Platform TOS/NC/NCI/SECNCI Combination Order Matrix Acquired West Virginia Service Territory

Type of Service (LSR.TOS)	Network Channel Code (LSR.NC)	Network Channel Interface Code (LSR.NCI)	Secondary Network Channel Interface Code (LSR.SECNCI)	Description
2ABL	(Blank)	(Blank)	(Blank)	Disconnect or Change Shared Broadband + Voice (when change impacts BB) Res with hunting (ACT=C; ACT=D)
1BBS	(Blank)	(Blank)	(Blank)	Business standalone broadband (all ACTs)
2BBS	(Blank)	(Blank)	(Blank)	Residential standalone broadband (all ACTs)
16M-	(Blank)	(Blank)	(Blank)	Business Bus NID move
26M-	(Blank)	(Blank)	(Blank)	Residential NID move

**NOTES:**

Only valid TOS/NC/NCI and SECNCI (when applicable) in the territory the service is located in will be accepted. Where (Blank) is indicated, the field must be left unpopulated. If values are populated this will result in a rejected PON. Please follow proper business rules for SLI field population.

<sup>1</sup>Not supported on ACT V.

<sup>2</sup> NC/NCI codes are not required on DB ACT J

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Revised: 06/12/2018



# Change Log

Date	Section	Change
6/12/2018	All	Added to notes: <i>1Not supported on ACT V and 2 NC/NCI codes are not required on DB ACT</i> Jeffective per June 17, 2018 Business Rule release. Added change log to document.