



# LNP Troubleshooting and Trigger Guide

## Contents

<b><i>LNP Troubleshooting</i></b> .....	<b>2</b>
Overview .....	2
LSR Request Types .....	2
Local Number Portability Center .....	2
<b><i>Ported Number Problems</i></b> .....	<b>3</b>
No dial tone and SPID = FTR .....	3
Only Local Frontier callers receive and out of service recording .....	4
All Calls to Ported TN gets a fast busy/call cannot be completed recording .....	5
NNSP requests translations be removed from Frontier’s switch.....	5
End-User getting billed by Frontier & CLEC.....	5
NNSP requests cancel after the TN has ported .....	6
<b><i>LNP Triggers</i></b> .....	<b>7</b>
Triggers – What, Why, When .....	7
<b><i>Change Log</i></b> .....	<b>8</b>

Frontier Wholesale

Jurisdiction: All  
Revised Date: 6/30/2021



# LNP Troubleshooting and Trigger Guide

## LNP Troubleshooting

---

### Overview

This document serves as a troubleshooting guide for Frontier Wholesale Customers with issues involving Local Number Portability (LNP.)

---

### LSR Request Types

This guide covers the BB/CB-V (Number Portability) REQ TYP for Frontier SPIDS 0121, 0161, 2473 and 5200.

---

### Local Number Portability Center

Frontier's Local Number Portability Center manages the processes that are necessary to provide the NPAC with accurate service provider identification. The LNP center performs Service Order Administration SOA tasks during the porting of a number, whether from Frontier to NNSP (New Network Service Provider) or NNSP to Frontier. Contact and escalation information for the LNP Center is available on the LSR Contact and Escalation List available from the Local Voice/UNE Services Contacts page of the Frontier Wholesale Website at: <https://wholesale.frontier.com/contacts-and-escalation-lists/voice-une-services-contacts>.

---



# LNP Troubleshooting and Trigger Guide

## Ported Number Problems

No dial tone  
and SPID =  
FTR

Problem	Instruction							
Prior to the FOC Date	Frontier may have been removed from the switch early. <ol style="list-style-type: none"> <li>1. FOC due date = future date</li> <li>2. Call Frontier LCSC at 888-608-8023</li> <li>3. Frontier LCSC Rep will verify status of TN in switch.</li> </ol>							
After the FOC due date	The NNSP may not have activated the TN on the FOC due date. <ol style="list-style-type: none"> <li>1. FOC due date = past due</li> <li>2. NNSP should activate the TN in SOA</li> </ol>							
After the BCN is received in VFO	Then end-user does not have a dial tone and SPID = FTR <table border="1" data-bbox="574 892 1317 1205"> <thead> <tr> <th>If...</th> <th>Then...</th> </tr> </thead> <tbody> <tr> <td> <ul style="list-style-type: none"> <li>• The end user wishes to have service through Frontier.</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• The end user calls Frontier retail customer service.</li> </ul> </td> </tr> <tr> <td> <ul style="list-style-type: none"> <li>• The end user wishes to have service through the NNSP</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• NNSP should coordinate activation of services with end user.</li> </ul> </td> </tr> </tbody> </table>		If...	Then...	<ul style="list-style-type: none"> <li>• The end user wishes to have service through Frontier.</li> </ul>	<ul style="list-style-type: none"> <li>• The end user calls Frontier retail customer service.</li> </ul>	<ul style="list-style-type: none"> <li>• The end user wishes to have service through the NNSP</li> </ul>	<ul style="list-style-type: none"> <li>• NNSP should coordinate activation of services with end user.</li> </ul>
If...	Then...							
<ul style="list-style-type: none"> <li>• The end user wishes to have service through Frontier.</li> </ul>	<ul style="list-style-type: none"> <li>• The end user calls Frontier retail customer service.</li> </ul>							
<ul style="list-style-type: none"> <li>• The end user wishes to have service through the NNSP</li> </ul>	<ul style="list-style-type: none"> <li>• NNSP should coordinate activation of services with end user.</li> </ul>							

*Continued on next page*



# LNP Troubleshooting and Trigger Guide

Only Local Frontier callers receive and out of service recording

Problem	Instruction						
Prior to FOC due date.	<p>The NNSP may have ported the TN early.</p> <ol style="list-style-type: none"> <li>1. FOC due date = future date.</li> <li>2. SPID = NNSP</li> <li>3. The NNSP must return the TN to Frontier in SOA until the FOC due date.</li> </ol>						
On the FOC due date	<p>Frontier may not have added the LNP Trigger.</p> <ol style="list-style-type: none"> <li>1. FOC due date = today.</li> <li>2. SPID = NNSP</li> <li>3. Call Frontier LCSC at 888-608-8023 to verify the LNP Trigger has been set.</li> <li>4. Follow the action in this chart.</li> </ol> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="background-color: #333; color: white;">If...</th> <th style="background-color: #333; color: white;">Then...</th> </tr> </thead> <tbody> <tr> <td> <ul style="list-style-type: none"> <li>• Trigger was added.</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• There is no action to take. The trigger was added, and the end user should have no issues.</li> </ul> </td> </tr> <tr> <td> <ul style="list-style-type: none"> <li>• Trigger was not added.</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• Frontier LCSC Rep will have translations removed completely from switch</li> </ul> </td> </tr> </tbody> </table>	If...	Then...	<ul style="list-style-type: none"> <li>• Trigger was added.</li> </ul>	<ul style="list-style-type: none"> <li>• There is no action to take. The trigger was added, and the end user should have no issues.</li> </ul>	<ul style="list-style-type: none"> <li>• Trigger was not added.</li> </ul>	<ul style="list-style-type: none"> <li>• Frontier LCSC Rep will have translations removed completely from switch</li> </ul>
If...	Then...						
<ul style="list-style-type: none"> <li>• Trigger was added.</li> </ul>	<ul style="list-style-type: none"> <li>• There is no action to take. The trigger was added, and the end user should have no issues.</li> </ul>						
<ul style="list-style-type: none"> <li>• Trigger was not added.</li> </ul>	<ul style="list-style-type: none"> <li>• Frontier LCSC Rep will have translations removed completely from switch</li> </ul>						
After FOC due date	<p>Frontier may not have removed the LNP trigger and translations in the switch.</p> <ol style="list-style-type: none"> <li>1. FOC due date = past due</li> <li>2. SPID = NNSP</li> <li>3. NNSP contacts Frontier LCSC at 888-608-8023 to verify translations were removed.</li> <li>4. Follow the action in this chart.</li> </ol> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="background-color: #333; color: white;">If...</th> <th style="background-color: #333; color: white;">Then...</th> </tr> </thead> <tbody> <tr> <td> <ul style="list-style-type: none"> <li>• All translations were removed.</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• No action needed</li> </ul> </td> </tr> <tr> <td> <ul style="list-style-type: none"> <li>• Translations were not removed.</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• Frontier LCSC rep will call Assignments and have translations removed completely from switch</li> </ul> </td> </tr> </tbody> </table>	If...	Then...	<ul style="list-style-type: none"> <li>• All translations were removed.</li> </ul>	<ul style="list-style-type: none"> <li>• No action needed</li> </ul>	<ul style="list-style-type: none"> <li>• Translations were not removed.</li> </ul>	<ul style="list-style-type: none"> <li>• Frontier LCSC rep will call Assignments and have translations removed completely from switch</li> </ul>
If...	Then...						
<ul style="list-style-type: none"> <li>• All translations were removed.</li> </ul>	<ul style="list-style-type: none"> <li>• No action needed</li> </ul>						
<ul style="list-style-type: none"> <li>• Translations were not removed.</li> </ul>	<ul style="list-style-type: none"> <li>• Frontier LCSC rep will call Assignments and have translations removed completely from switch</li> </ul>						

*Continued on next page*



## LNP Troubleshooting and Trigger Guide

All Calls to Ported TN gets a fast busy/call cannot be completed recording

Problem	Instruction
After FOC due date	<p>The NNSP may not have built the TN their own switch.</p> <ol style="list-style-type: none"> <li>1. Verify FOC due date = past due.</li> <li>2. SPID = NNSP</li> <li>3. NNSP builds TN in their switch</li> </ol>

NNSP requests translations be removed from **Frontier's** switch

Problem	Instruction						
On FOC due date	<ol style="list-style-type: none"> <li>1. FOC due date = today</li> <li>2. SPID = FTR</li> <li>3. NNSP calls Frontier LCSC at 888-608-8023</li> </ol> <table border="1"> <thead> <tr> <th>If...</th> <th>Then...</th> </tr> </thead> <tbody> <tr> <td> <ul style="list-style-type: none"> <li>• PON did not request coordination (DFDT or CHC)</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• No Action is taken. Translations will be removed the day after the port</li> </ul> </td> </tr> <tr> <td> <ul style="list-style-type: none"> <li>• PON did request coordination, (DFDT or CHC)</li> </ul> </td> <td> <ul style="list-style-type: none"> <li>• Frontier LCSC rep will contact CSSC to remove translations</li> </ul> </td> </tr> </tbody> </table>	If...	Then...	<ul style="list-style-type: none"> <li>• PON did not request coordination (DFDT or CHC)</li> </ul>	<ul style="list-style-type: none"> <li>• No Action is taken. Translations will be removed the day after the port</li> </ul>	<ul style="list-style-type: none"> <li>• PON did request coordination, (DFDT or CHC)</li> </ul>	<ul style="list-style-type: none"> <li>• Frontier LCSC rep will contact CSSC to remove translations</li> </ul>
If...	Then...						
<ul style="list-style-type: none"> <li>• PON did not request coordination (DFDT or CHC)</li> </ul>	<ul style="list-style-type: none"> <li>• No Action is taken. Translations will be removed the day after the port</li> </ul>						
<ul style="list-style-type: none"> <li>• PON did request coordination, (DFDT or CHC)</li> </ul>	<ul style="list-style-type: none"> <li>• Frontier LCSC rep will contact CSSC to remove translations</li> </ul>						

End-User getting billed by Frontier & CLEC

Problem	Instruction
After BCN is sent to CLEC	<p>Frontier is still billing for a ported out number.</p> <ol style="list-style-type: none"> <li>1. FOC due date = past due</li> <li>2. PON status in VFO = BCN</li> <li>3. SPID = NNSP</li> <li>4. NNSP calls Frontier LCSC at 888-608-8023. Frontier LCSC rep will create service orders to end billing.</li> </ol>

*Continued on next page*



# LNP Troubleshooting and Trigger Guide

NNSP requests cancel after the TN has ported

Problem	Instruction
On FOC due date	<ol style="list-style-type: none"><li>1. FOC due date = today</li><li>2. PON status in VFO = FOC</li><li>3. SPID = NNSP</li><li>4. NNSP submits a sup 1 in VFO</li><li>5. NNSP contacts Frontier LCSC at 888-608-8023 to advise of short notice sup allowing Frontier LCSC rep to process the sup 1 immediately</li><li>6. NNSP contacts the LNP Center to negotiate the return of the TN in SOA. Contact and escalation information for the LNP Center is available on the LSR Contact and Escalation List available from the Local Voice/UNE Services Contacts page of the Frontier Wholesale Operations Website at: <a href="https://wholesale.frontier.com/contacts-and-escalation-lists/voice-une-services-contacts">https://wholesale.frontier.com/contacts-and-escalation-lists/voice-une-services-contacts</a>.</li></ol>
Within 24 hours of FOC Due Date	<ol style="list-style-type: none"><li>1. FOC due date is no more than 24 hours past</li><li>2. PON status in VFO is FOC or PCN</li><li>3. SPID = NNSP</li><li>4. NNSP refers to <a href="#">Throwback and CLEC Disconnect in Error Process</a></li><li>5. NNSP refers to <a href="#">Supplements Submitted on CDD</a></li></ol>



# LNP Troubleshooting and Trigger Guide

## LNP Triggers

Triggers –  
What, Why,  
When

Frontier places a 10-digit trigger on a telephone number that is in process of being ported to a NNSP per industry standards. In simple terms, a trigger allows Frontier to set up automated programming that prepares the number to be released to the NNSP on the date requested, the FOC due date. During this time, the end user can make and receive calls until the NNSP provisions the new service in its system. After the due date, the trigger and line is removed from the FTR switch.

Automation is programmed to add and remove LNP triggers. When Automation fails, Frontier manually adds them via fallout report processes.

This is an overview of Frontier’s 10-trigger placement.

DD-1 means FOC due date minus one day (the day before the FOC due date.)

DD+1 means FOC due date plus one day (one day after the FOC due date.)

Product Type	Detail
POTS / Line side type service	<ul style="list-style-type: none"> <li data-bbox="683 984 1295 1052">• Trigger is added on Date Due minus 1 (DD-1). This includes one-day ports.</li> <li data-bbox="683 1087 1276 1155">• Line (translations) and trigger removed on Date Due plus 1 (DD+1).</li> </ul>
Other types: DID numbers, distinctive ring, independent voice mail, etc.	10-digit triggers do not apply to trunk side services.



# LNP Troubleshooting and Trigger Guide

## Change Log

Date	Page Number	Change
3/01/2017	8	Changed info in parenthesis to (DD+1) and updated meaning for Due Date + 1.
10/26/2017		Updated embedded links to secured URLs
06/30/2021	All	Update embedded links

*Continued on next page*

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.