

#### **Contents**

Product Description	2
ASR Fields used for validating PONs	3
ASR Example	4
Change Log	7

#### Frontier Wholesale

Jurisdiction: All

Effective Date: 08/21/2015 Revised Date: 6/15/2024



### **Product Description**

This service will be a point-to-point wavelength product and purchased to support the need for managed optical transport across our shared optical network. This product will dedicate one wavelength for each point-to-point circuit and can be used to connect a Customer designated premise to a Customer Point of Presence (POP) or to interconnect POP locations.

### **Order Submission Eligibility**

Prior to submitting a Frontier Wavelength order, a valid Frontier Wavelength Contract must be obtained from your Frontier Sales Team. If you are unaware of your assigned dedicated Sales Team, send an email to <a href="https://www.wholesale\_Inquiry@ftr.com">Wholesale\_Inquiry@ftr.com</a>.

Once a Frontier Wavelength Contract is obtained, validate the Wavelength speed is within your Wavelength Contract.

#### **To Verify Eligibility:**

- Determine the Serving Wire Center (SWC) for both A and Z locations. If needed, use <u>ASR</u>
   <u>Pre-Order Location Inquiry</u> to determine the SWC,
- Access the <u>Ethernet\_Enabled\_SWC</u> List.
  - o Filter on the "SWC" column.
  - Find the column labeled "10G & 100G Wavelength" or "400G Wavelength" and verify the column contains a "Y".

#### An order *is* eligible for order submission when:

• The SWC for both A and Z locations contains a "Y" in the "10G & 100G Wavelength" column and are within the same LATA.

#### An order *is not* eligible for order submission when:

- The SWC for either A or Z locations is not found on the Ethernet\_Enabled SWC List.
- The SWC for either A or Z locations does not contain a "Y" in the "10G & 100G Wavelenth" column.
- The SWC for either A or Z locations contains a "Y" in the "400G Wavelength" column.
- The SWC for both A or Z locations contains a "Y" in the "10G &100G Wavelength" column and are <u>not</u> within the same LATA. (Note: If locations in two different Frontier entities, each ICSC code for each entity must be populated on the order.)

For orders not eligible for order submission, please contact your assigned Sales Team to obtain a request for pricing.



## **ASR Fields used for validating PONs**

Field	Description/Value	
VTA	12, 24, 36, 60, 84, or 120	
SPEC Code	VELTEN	
PNUM	POS 1-3 'VEL' or 'FOT' followed by Contract Number or ICB Number	
FORMS	Transport	



## **ASR Example**

Frontier Wavelength REQTYP SD, ACT = N

➤ VFO TYPE: SA-2 Point

New Connect to establish FOTS Point to Point Enduser to Enduser				
Administrative Form				
Key ASR Field	Value			
DDD	Negotiated (Submit with minimum 18 day interval) Best Date will be returned on FOC			
REQTYP	SD			
ACT	N			
QSA	01			
EXP	Populate only if Expedite is being requested			
RTR	S, F or N			
PIU	100			
QTY	1			
ACTL	Required – Must be a valid Special Access or Collocated ACTL			
BAN	E, N or Valid CABS BAN			
SPEC	VELTEN			
ASC-EC	Required if more than one LEC is involved on NECA Route			



Bill Form		
ACNA	Identifies the COMMON LANGUAGE IAC code for the customer who should receive the bill for the ordered service	
FUSF	Federal Universal Service Fee (FUSF). 1 alpha character Valid Values: E = Exempt Federal Universal Service Fee, N = Non-Exempt (Assessed) Federal Universal Service Fee	
VTA	12, 24, 36, 60, 84, or 120	
PNUM	POS 1-3 = FOT or VEL	
Contact		
INIT	Identifies the customer who originated the request	
INITIATOR TEL	Telephone number of customer who originated the request	
INIT EMAIL	Required. Identifies the electronic mail address of the initiator	
DSGCON	Identifies the employee of the customer or agent who should be contacted on design/engineering/translation issues and to whom the Design Layout Report may be sent. Required when RTR is F or S	
DSGCON TEL	Telephone number of employee of the customer or agent who should be contacted on design/engineering issues	
IMPCON	Identifies the customer employee or office responsible installation and completion	
IMPCON TEL	Identifies the telephone number of the implementation contact	



Transport Form				
NC	Refer to NC/NCI/SECNCI Job-aid: Frontier Wavelength			
NCI	Refer to NC/NCI/SECNCI Job-aid: Frontier Wavelength			
S25	А			
SECNCI	Refer to NC/NCI/SECNCI Job-aid: Frontier Wavelength			
SECLOC	E			
CCEA	Required if Collocated ACTL			
SR	Refer to NC/NCI/SECNCI Job-aid: Frontier Wavelength Required			
Service Address Location Information (SALI) for Secondary Location				
EUNAME	Identifies the end user name associated with the Secondary location			
SANO	Address Number			
SASF	Address Number Suffix			
SASD	Street Directional Prefix			
SASN	Street Name			
LD1,2,3	Identifies additional information related to the service address. (e.g., building, floor, room)			
LV1,2,3	Identifies the value associated with the Location Designator of the service address.			
CITY	City			
SATH	Street Type			
SASS	Street Directional Suffix			
STATE	State			
ZIP CODE	Zip Code			



### **Change Log**

Date	Page Number	Change
08/21/2015	Original	
03/29/2018	varies	Updated to correct PNUM and layout
02/20/2020	Page 4	Change REQTYP to SD
10/16/2023 Var	Varies	Added VTA of 84 and 120, provided
		link to NC/NCI job-aid
10/20/2023	All	Revise product name – change from
	All	FOTS to Frontier Wavelength
06/15/2024	2	Add 400G

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBLITY OF SUCH DAMAGES.